

# Polludrone®

### Ambient Air Quality Monitoring System

Polludrone is a Continuous Ambient Air Quality Monitoring System (CAAQMS). It is capable of monitoring various environmental parameters related to air quality, noise, odour, weather, radiation etc. It measures the particulate matter and gaseous concentrations in the ambient air in real-time. Using external probes, it can also monitor other auxiliary parameters like traffic, disaster etc.

Polludrone is an ideal choice for smart cities as well as urban infrastructure applications like roadside, campus, and airport monitoring. It is easily integrable with a Smart Pole/Intelligent Pole.

### **Product Variants**

Variant Name	Application	Parameter			
Polludrone Lite	General Purpose	PM2.5, PM10, CO2, CO, Noise, Light, UV-Radiation, Temperature, Humidity			
Polludrone Smart	Extensive	PM2.5, PM10, CO2, CO, SO2, NO, NO2, O3, Noise, Light, UV-Radiation, Temperature, Humidity			
Polludrone Pro	Critical	PM1, PM2.5, PM10, PM100 (TSP), CO2, CO, SO2, NO, NO2, O3, H2S, Noise, Light, UV-Radiation, Temperature, Humidity			
External Modules	Optional	Wind Speed & Direction, Rainfall, Flood (integrable with all the 3 variant			





Smart City Pollution monitoring at strategic locations in a smart-city empowers city authorities to obtain actionable insights for pollution control.



**Campus Monitoring** Pollution monitoring at key locations on campus allows stakeholders to spread awareness about environmental conditions of the premises.



Road-side & Tunnels Pollution monitoring at roads and tunnels can help create pollution mitigation action plan to control vehicular emissions.



#### Airports

Pollution and noise monitoring at taxiways and terminal surroundings facilitates airport authorities to analyze its impact on travellers and surrounding neighbourhoods





### **Product Features**

Patented Technology: Works on innovative
e-breathing technology for higher data accuracy



**Solar Powered with Battery Backup:** Compatible to charge internal battery using solar power



**Retrofit Design:** Plug and play design for ease of implementation



**Compact:** Light-weight and compact system that can be installed at 12-15 feet (4-5 m) height



**Ultimate Durability:** Made of high-grade engineering-metal and composite polymers for long life

Identity & Configuration: Each equipment carries its unique identity with geo-tagging through wireless configuration



Weather Resistant: IP66 Grade (certified) enclosure for endurance against harsh weather conditions



Tamper Proof: Comes with a security system to avoid tampering / malfunction / sabotage



**Over-The-Air Update:** Automatically upgradeable from a central server without any onsite visit



**Real-Time Data:** Continuous monitoring and real-time data transfer at configurable intervals



Network Agnostic: Supports a wide range of connectivity options like GSM / GPRS / WiFi / LoRa / NBIoT/ Ethernet / Modbus



**On-device Calibration:** On-site device calibration capability using on-device calibration software

### **3 Levels of Calibration**



Factory Calibration The sensors are bump tested at Oizom factory to check their proper functioning for each parameter.



Lab Calibration Laboratory calibration is performed for Baseline Correction & Span-Calibration for all the parameters to compensate for cross-sensitivity and ensure higher data accuracy.



Collocation Calibration The sensors are calibrated against a reference station before installation and their performance is tested in the ambient condition before final deployment.

## **General Specifications**

Size	360mm (H) x 328mm (W) x 200mm (D)			
Weight	7.2 Kg (instrument weight)			
Material	Aluminum Magnesium Alloy, Mild-steel (With Powder Coating), FRP			
Certifications	CE & FCC Certified, PTCRB Certified Communication Module			



# Communication

Data Interval	2-30 minutes (configurable)
Data-push Protocol	HTTP post request to host-server
Data-pull	HTTP request on device IP
Firmware Updates	Over-The-Air Firmware Update
Standby Connectivity	GSM (2G/3G/4G) for remote diagnosis FOTA updates, and cloud calibration

#### Power

Avg. Power Consumption	5 Watt (Actual consumption depends upon the number of parameters)
Power Input Options	External 110-230V AC 50-60Hz, 40Watt Monocrystal Solar Panel
SMPS Specs	24V, 2Amps output UL-62368 & CAN/CSA C22.2 Certified
Battery Backup Time	12 Hours
Battery Specs	Lithium iron phosphate (LiFePO4) battery cell with rated voltage 12.8V Capacity 6Ah

# **Technical Specification**

Processor	Quad Core ARM Cortex			
Memory	2GB RAM / 8GB eMMC ROM			
Device Interface	On-device Software / API			
Operating Temperature	-20 °C to 60 °C			
Operating Humidity	0-95% RH			

	Connectivity Options	Specification
Wireless	GSM LORA LTE NB-lot Sigfox Wifi	Global 2G / 3G / 4G 868 MHz / 915 MHz CAT-M1 CAT-NB1 868 to 869 MHz, 902 to 928 MHz AP Mode and Station Mode
Wired	Ethernet Modbus Relay Output	Static / DHCP Configuration RS485 RTU / TCP 2 Channel

### **Parameters**

ID	Parameter	Range	Resolution	Min. Detection	Error / Drift	Working Principle	Measurement Principle	Sample Rate	Expected Sensor Life
PM2.5	Suspended Particulate Matters with size less than 2.5µ	Upto 5000 µg/m³	0.1 µg/m³	1 µg/m³	Upto ±10 %	Optical Particle Counter		1 L /min	12 months
ΡΜιο	Suspended Particulate Matters with size less than 10µ								
ΡMι	Ultra Fine Particulate Matters with size less than 1µ								
PM100	Total Suspended Particulates (TSP)	Upto 30000 µg/m³							
CO <sub>2</sub>	Carbon Dioxide	Up to 5000 ppm	1 ppm	20 ppm	< ±5 ppm / Year	NDIR	Active	325 mL per sample	3 years
со	Carbon Monoxide	0-1000 ppm	10 ppb	100 ppb	< ±100 ppb / Year	Electrochemical	Sampling		2 years
SO <sub>2</sub>	Sulfur Dioxide	0-20 ppm	1 ppb	10 ppb	< ±20 ppb / Year				
NO	Nitric Oxide	0-20 ppm	1 ppb	10 ppb	< ±50 ppb / Year				
NO <sub>2</sub>	Nitrogen Dioxide	0-20 ppm	1 ppb	10 ppb	< ±20 ppb / Year				
O <sub>3</sub>	Ozone	0-20 ppm	1 ppb	10 ppb	< ±20 ppb / Year				
H₂S	Hydrogen Sulfide	0-100 ppm	1 ppb	10 ppb	< ±100 ppb / Year				
Noise	Ambient Noise	Upto 140 dB	1dB	30 dB	2% / Year	Capacitance			
Li	Light Intensity	Up to 1,00,000 Lux	1 Lux	1 Lux	N.A.	Photo- conductivity Passive Monitoring			
UV	UV Radiation (0-12 UVI)	0.1-100,000 uW/cm²	0.1 uW/cm <sup>2</sup>	0.1 uW/cm <sup>2</sup>	N.A.				3 years
Lv	Visible Light Intensity	Up to 5000 Lux	0.1 Lux	0.1 Lux	N.A.		Passive Monitoring	N.A.	
Temp	Temperature	-40 to 125 °C	0.01°C	-40 °C	N.A.	Solid state semi conductor sensing	1		
Hum	Humidity	Up to 100% Rh	0.1%	0.1%	N.A.				
Bmp	Barometric Pressure	300-1100 hPa	0.18 Pa	300 hPa	±1.0 hPa / Year				

# **External Modules** 0

(optional)

**Rain Sensor** 🗞 Tipping Bucket 🞯 In mm / inch



2

Wind Sensor 🗞 Ultrasonic sensor 🞯 360°, 0-40 m/s



Flood Sensor

🗞 Ultrasonic sensor 🞯 Upto 765 cm

# **Functional Specification**

#### **Strategic Location Selection:**

Proper location selection is critical for optimized data collection. It varies as per the purpose of the project. According to USEPA QA handbook (Vol II, Section 6.0 Rev.1), the selection of locations should be based on monitoring purposes such as:

Pole / Wall (preferably 270° open surrounding)

As per maximum direct sunlight exposure

(if ambient-light monitoring is a preference) Constant AC supply within a 2-meter range

12-15 feet (4-5 meters)

from the unit or solar panel

Uninterrupted network connection

- Real-time air quality public reporting
- Research monitoring
- Trends monitoring
- Compliance monitoring
- Emergency episode monitoring

#### Installation:

Preferred Mounting

Installation Height

Power Availability

Network Availability

Direction

12-15 ft height From the Ground level	270° Open surrounding

# Operation:

When the device is powered on, the device intakes air samples at a predefined frequency through the air sampling system. Once the air sample is stabilized, the sensory system takes multiple readings during the sampling time and performs relevant data-processing. During this cycle time, the device flushes out old air sample and pulls in a fresh one. After each sampling, the data processing system sends the processed data to the central server using a built-in communication module

#### Maintenance:

<sup>7</sup> **Cleaning:** Periodic cleaning is important to ensure optimum device performance. Monthly or quarterly regular maintenance activity has to be carried out depending upon the surrounding. The activity includes cleaning the dome for the light sensor, air inlet, and outlet mesh & general cleaning of the exterior.

Sensor Replacement: Every sensor has a limited life span. The sensor life depends on the average pollutant concentration in the area. The sensors need to be replaced once their performance starts to deteriorate and the system starts giving unstable data.



**Spot-Calibration:** The frequency of calibration is decided based on atmospheric conditions and individual sensor drift to ensure data accuracy. Spot calibration can be performed using reference equipment which can also be a recently calibrated Oizom device.

**Diagnosis/Debugging:** Power and network availability are the prime check in case of equipment failure. If the issue is still unresolved after remote diagnosis, on-site troubleshooting can be planned by an engineer.

#### .

306, Indraprasth Corporate, Prahladnagar, Ahmedabad - India

contact@oizom.com / connect@oizom.com

+91-8866660025 / 82



HB9, Savoie Technolac, Le Bourget du Lac - France ■ hello@oizom.com ↓ +33 783426695

